



FEATURES

- "F-Connect" design for heatsink and optics.
- Fit in most of MR16 LED downlight converters.
- Flicker-free external driver.
- Compatible with leading and trailing edge phase cut dimmers.
- 5-year guarantee.

Technical Data

Input Voltage/Hz	AC200-240V 50/60Hz
Output Voltage/Current	DC34V/130mA
Power	6W
Rated Input Current	0.03A
THD	<6%
PF value	>0.85
Ingress Protection	IP40
Operating Temperature	-10-40°C
Dimmability	Triac dimmable with DIMMATE driver

Optical Data

LED Brand	Bridgelux COB LED
CRI	Ra>80, Ra>90
Beam Angle	18°/24°/38°/50°
Colour temperatures	2700K/3000K/4000K
System luminous efficacy up to	117lm/W

Packaging

Box Dimensions	L195 x W70 x H96 mm
Box Net Weight	0.236Kg
Box Gross Weight	0.293Kg
Carton Dimensions	L410 x W375 x H405 mm/40 PCS
Carton Net Weight	9.44Kg
Carton Gross Weight	12.92Kg



CCT		Beam Angle	Lumen	Efficacy		Beam Angle	Lumen	Efficacy
2700K	CRI 80+	18°	583lm	104lm/W	CRI 90+	18°	475lm	86lm/W
		24°	599lm	108lm/W		24°	490lm	89lm/W
		38°	600lm	108lm/W		38°	488lm	89lm/W
		50°	576lm	103lm/W		50°	468lm	85lm/W
3000K		18°	597lm	107lm/W		18°	508lm	91lm/W
		24°	614lm	111lm/W		24°	525lm	95lm/W
		38°	616lm	111lm/W		38°	523lm	94lm/W
		50°	589lm	106lm/W		50°	502lm	90lm/W
4000K		18°	628lm	113lm/W		18°	543lm	99lm/W
		24°	646lm	116lm/W		24°	559lm	102lm/W
		38°	651lm	117lm/W		38°	558lm	101lm/W
		50°	622lm	111lm/W		50°	536lm	97lm/W

ECLIPSE CONSEIL

Siège : +33 (1) 79 30 48 19- Showroom Paris : +33 (1) 78 95 50 14 - Mob : +33 (6) 87 82 12 04
Siège social : 7 rue Prudent Neel 92500 Rueil-Malmaison - Showroom : 1 rue Dulong 75017 PARIS