



## FEATURES

- "F-Connect" design for heatsink and optics.
- Fit in most of MR16 LED downlight converters.
- Flicker-free external driver.
- Compatible with leading and trailing edge phase cut dimmers.
- 5-year guarantee.

## Technical Data

Input Voltage/Hz	AC200-240V 50/60Hz
Output Voltage/Current	DC34V/300mA
Power	13W
Rated Input Current	0.065A
PF value	>0.9
Ingress Protection	IP40
Operating Temperature	-10—40℃
Dimmability	Triac dimmable with <b>DIMMATE</b> driver

## Optical Data

LED Brand	Bridgelux COB LED
CRI	Ra> 80, Ra> 90
Beam Angle	15°/25°/38°/60°
Colour temperatures	2700K/3000K/4000K
System luminous efficacy up to	117lm/W

## Packaging

Box Dimensions	L195 x W70 x H96 mm
Box Net Weight	0.288Kg
Box Gross Weight	0.345Kg
Carton Dimensions	L410 x W375 x H405 mm/40 PCS
Carton Net Weight	11.52Kg
Carton Gross Weight	13.76Kg



CCT		Beam Angle	Lumen	Efficacy		Beam Angle	Lumen	Efficacy
2700K	CRI 80+	15°	1194lm	94lm/W	CRI 90+	15°	991lm	80lm/W
		25°	1168lm	94lm/W		25°	983lm	80lm/W
		38°	1180lm	95lm/W		38°	985lm	80lm/W
		60°	1175lm	95lm/W		60°	1004lm	81lm/W
3000K		15°	1458lm	117lm/W		15°	1141lm	91lm/W
		25°	1442lm	115lm/W		25°	1134lm	89lm/W
		38°	1459lm	116lm/W		38°	1124lm	89lm/W
		60°	1443lm	116lm/W		60°	1128lm	89lm/W
4000K		15°	1413lm	113lm/W		15°	1242lm	98lm/W
		25°	1398lm	112lm/W		25°	1207lm	97lm/W
		38°	1463lm	117lm/W		38°	1294lm	104lm/W
		60°	1459lm	117lm/W		60°	1286lm	103lm/W

## ECLIPSE CONSEIL

Siège : +33 (1) 79 30 48 19- Showroom Paris : +33 (1) 78 95 50 14 - Mob : +33 (6) 87 82 12 04  
Siège social : 7 rue Prudent Neel 92500 Rueil-Malmaison - Showroom : 1 rue Dulong 75017 PARIS