



FEATURES

- "F-Connect" design for heatsink and optics.
- Fit in most of MR16 LED downlight converters.
- Flicker-free external driver.
- Compatible with leading and trailing edge phase cut dimmers.
- 5-year guarantee.

Technical Data

Input Voltage/Hz	AC200-240V 50/60Hz
Output Voltage/Current	DC34V/300mA
Power	13W
Rated Input Current	0.065A
PF value	>0.9
Ingress Protection	IP40
Operating Temperature	-10-40°C
Dimmability	Triac dimmable with DIMMATE driver

Optical Data

LED Brand	Bridgelux COB LED
CRI	Ra > 80, Ra > 90
Beam Angle	15°/24°/36°/60°
Colour temperatures	2700K/3000K/4000K
System luminous efficacy up to	120lm/W

Packaging

Box Dimensions	L195 x W70 x H96 mm
Box Net Weight	0.286Kg
Box Gross Weight	0.343Kg
Carton Dimensions	L410 x W375 x H405 mm/40 PCS
Carton Net Weight	11.44Kg
Carton Gross Weight	13.7Kg



CCT		Beam Angle	Lumen	Efficacy		Beam Angle	Lumen	Efficacy		
2700K	CRI 80+	15°	1119lm	90lm/W	CRI 90+	15°	953lm	75lm/W		
		24°	1214lm	98lm/W		24°	965lm	78lm/W		
		36°	1217lm	98lm/W		36°	1040lm	84lm/W		
		60°	1242lm	100lm/W		60°	1056lm	85lm/W		
3000K		15°	1429lm	114lm/W		90+	15°	1096lm	87lm/W	
		24°	1453lm	116lm/W			24°	1189lm	95lm/W	
		36°	1452lm	116lm/W			36°	1184lm	94lm/W	
		60°	1482lm	119lm/W			60°	1206lm	96lm/W	
4000K		15°	1419lm	111lm/W				15°	1178lm	95lm/W
		24°	1437lm	115lm/W				24°	1216lm	98lm/W
		36°	1483lm	119lm/W				36°	1275lm	103lm/W
		60°	1517lm	120lm/W				60°	1280lm	103lm/W

ECLIPSE CONSEIL

Siège : +33 (1) 79 30 48 19- Showroom Paris : +33 (1) 78 95 50 14 - Mob : +33 (6) 87 82 12 04
Siège social : 7 rue Prudent Neel 92500 Rueil-Malmaison - Showroom : 1 rue Dulong 75017 PARIS